

The Funke HADSC 100 is a set of two revolutionary small sized antennas for digital and analog TV reception which are easy to install and work with any diversity application. The innovative technology, quality and solid design make the Funke HADSC 100 a modern and reliable TV partner for you!



General specifications

Funke art. nr.	294.201502
Preferred applications	Mobile reception
Amplifier principle	Low noise single stage amplifier
Connection	3,5 m flexible coaxial cable with IEC-male connector

Technical specifications

Output impedance	75 Ω
Frequency range	174 – 230 MHz 470 – 862 MHz
Channels (CCIR)	VHF 5 - 12 UHF 21 – 69
Antenna gain	5 - 10 dBi typ.
Beamwidth	360°
Input voltage	5 ± 0,5 V
Input current	30 mA typ.



Physical specifications

Dimensions Antenna (l x w x h)	132 x 17 x 6,5 mm
Weight Antenna (incl. cable)	0,135 kg
Colour	Black
Dimensions Package (l x w x h)	65 x 140 x 166 mm
Weight Package	0,166 kg
Outer Carton	40
Pallet	1000

Contents

- HADSC 100
- Cable 2,5 m
- User Manual

Clearly the Best

